

iPhone Bluetooth Recorder V1.00

User Manual



1. Features of product

- Build in Bluetooth 4.2, ultra-low power consumption.
- Connect Bluetooth to call, avoid the radiation effectively.
- Dialing distances can reach about 10 m.
- Has the voice prompt during operation, more considerate.
- Build in cycle delete function, no need to delete files manually.
- Build in 200mAh lithium battery.

2. Features of function

- Recording automatically when get through, and stop recording when hang up.
- Automatic voice response systems so that you can have personal space not only to avoid bother, but also won't miss the important events.
- Build in clock chip, recording files named according to the time.
- Can copy the recording files out from the earphones connected to computer via USB cable.

3. Parameters

Working voltage: 5V

Shell material: ABS

Sleep current: $\leq 10\mu\text{A}$

Recording current: $\leq 70\text{mA}$

Environment: indoor only, relative humidity less than 95%.

4. Power on/off

The product is turned off by default when leaving the factory, long press 5s to be power on, it also has the voice prompt.

5. Bluetooth pairing connection

It will enter the pairing state automatically after power on, open the Bluetooth switch on your mobile phone, search device, tap the name 'WT1999' to connect. It should enter the password '1999' at the first time, it also has the voice prompt after connected.

6. Time update

1. In order to search for the files more exactly in the future, please update the build-in time in line with the current time when first use.

2. Create a new notepad(.txt) on the desktop, change the name into 'TM', open it, input the current time of YYMMDDHHMMSS, such as 20170119191919, means the current time setting is 19:19 on January 19th, 2017, 19 seconds.

3. Pull up the USB cable, now this product will update the current time and delete the notepad automatically.

7. Key function

Answer key:

1. Short press to answer the phone.
2. Short press to hang up.
3. Long press 5s for Power on/off.

Recording key:

1. Long press over 2s for Recording, short press to Stop.
2. Without any operation, short press for Play, press again for Pause.
3. Long press 5s for the Automatic voice response mode.
4. Press Previous and Next keys at the same time for 3s, delete all the recording.

Previous:

1. Short press for volume up when talking or listening to music.
2. Double press for previous song when listening.
3. Short press for previous recording when playing.
4. Long press for 3s for deleting the current recording.
5. Press with Record key at the same time for 3s for deleting all the recording.

Next:

1. Short press for volume down when talking or listening.
2. Double press for next song when listening.
3. Short press for next recording when playing.
4. Long press for 5s for Automatic recording/Manual recording mode.
5. Press with Record key at the same time for 3s to delete all.

Enter/quit automatic voice response mode

1. Long press the recording key for 5s, you can hear the 'automatic voice response mode has been opened', then it will enter the automatic voice response mode; When there is a call coming more than 3 seconds, it will answer the phone automatically and say 'Hello, I'm busy now, please leave a message after a beep. Beep...', then it will start to record, and stop recording automatically when the end of call. If user want to check that who had made call during this period, can short press the record key to play the recording.

2. The opposite side can not hear user's voice when automatic response. If user want to answer the phone during the automatic response, just press the record key. After answering the phone, it will turn back to record mode, should repeat the above steps next time.

8. Automatic recording/Manual recording Mode

1. This product can record automatically when get through, and stop recording when hang up.

2. Long press the previous key for 5s, can switch to the manual recording mode, need to long press the record key to start record. Continue to long press the previous key for 5s, it will have the voice prompt during operation.

9. Charging and exporting the recording files

1. Charging: Micro USB port for charging, with USB cable. If it is out of the power during using, it will have the prompt of 'low battery'. The blue light is on for a long time during charging, and off after it is charged fully. It takes about 2 hours.

2. Exporting the recording files: Connect to the computer via USB cable, will appear a removable disk. You can copy or delete the recording files in the disk. Attention please, do not delete the MP3 files of root directory in the memory card. Otherwise, this product can not work properly.

10. Notes of operation

1. The MP3 file in the memory card is a prompt tone, please do not delete, modify it or make any rearrangement. Otherwise, it will cause this product cannot work properly.

2. When it enter the automatic voice response mode, press the play key can quit this mode and switch to automatic recording mode.

3. Do not modify the suffix(.txt) of the notepad you created for time update. Only need to modify the name into 'TM'. It takes some time to edit and copy the files into this product, so please reserve some margin of error when you set the time. There will be some differences between the updated time and the actual time, but it is limited a few seconds.

4. If this product does not match the phone after enter the Bluetooth pairing mode, it will have an automatic shutdown within 2 mins. You need to turn it on again for using.

Indemnification

SHENZHEN WAYTRONIC ELECTRONIC CO.,LTD. reserves the right to modify and use information without prior notice to customers. New product specifications will be subject to the latest version.

Contact Us

Shenzhen Waytronic Electronics Co., Ltd.

Tel: +86-755-29605099

Fax : +86-755-29606626

Website: en.waytronic.com

E-mail: WT1999@waytronic.com

Add:4/F,Building No.11,Fuan Robotics Industrial Park, Fuyong,Baoan
District,Shenzhen ,518103,Guangdong ,China